



Features of True-RMS Digital Multimeter

	Range	Accuracy	
		PM890C	PM890D
DC Voltage	600mV/6V/60V/600V/1000V	+/- (5.0%+3)	+/- (5.0%+3)
AC Voltage	6V/60V/600V/1000V	+/- (0.8%+3)	+/- (0.8%+3)
DC Current	6uA/6mA/60mA/600mA	+/- (0.8%+3)	+/- (0.8%+3)
	20A	+/- (1.2%+3)	+/- (1.2%+3)
AC Current	6mA/60mA/600mA	+/- (1.0%+3)	+/- (1.0%+3)
	20A	+/- (1.5%+3)	+/- (1.5%+3)
Resistance	600Ohm/6kOhm/60kOhm/600kOhm/6MOhm	+/- (0.8%+3)	+/- (0.8%+3)
	60MOhm	+/- (1.2%+3)	+/- (1.2%+3)
Capacitance	6nF/60nF/600nF/6uF/60uF/600uF/6mF	+/- (4.0%+3)	+/- (4.0%+3)
	60mF	+/- (5.0%+3)	+/- (5.0%+3)
Frequency	60Hz/600Hz/6kHz/60kHz/600kHz/6Mhz/10MHz	+/- (1.0%+3)	+/- (1.0%+3)
Duty Cycle	5%~95%	+/- (2.0%+3)	+/- (2.0%+3)
Temperature	-20~1000°C/-4~1832°F	+/- (1.0%+3)	
hFE	0~1000	+/- (1.0%+3)	+/- (1.0%+3)
Feature	PM890C	PM890D	
Display	6000Counts	6000Counts	
True RMS	Yes	Yes	
ACV(bandwidth)	1kHz	1kHz	
°C/°F	Yes		
Frequency	10MHz	10MHz	
Resistance	60MOhm	60MOhm	
Capacitance	60mF	60mF	
Continuity	High/Medium/Low (LED signal indication)	High/Medium/Low (LED signal indication)	
Diode Test	Yes	Yes	
hFE	Yes	yes	
Live Line	High/Medium/Low (LED signal indication)	High/Medium/Low (LED signal indication)	
Low Battery Indication	Yes	Yes	
Auto Power off	yes	yes	

