

### 1.0A, Non-isolated SIP Package Switching Regulators

### Features

- Rated output current: 1A
- Non-isolated, step down switching regulators
- Input voltage range: 6.0~36VDC
- Regulated single output with low ripple and noise
- High efficiency up to 96%, no need for heatsink
- Low no load input current,0.3mA only

- Compatible with LM78 linear regulators RoHS compliant
- Short circuit protection
- Operating temperature range: -40 ~ +85°C ambient
- ► Meet IEC/EN/UL 62368-1
- > 3 year warranty





### Overview

The RM10SN series are non-isolated switching regulators, pin to pin compatible with LM78 family linear regulators. Unlike those linear regulators, the RM series switching regulators are high efficiency up to 96%. They do not need for any heatsink because very few energy is wasted as heat. Besides, these converters accept very wide input voltage range 6~36VDC, operate over wide ambient temperature range -40 ~ +85°C, and are short circuit and overheat protected. This particular series has very low no load input current, 0.3mA only. These converters are especially suitable for applications such portable devices, where energy saving, space saving and high performance are essential.

### **Model Numbers**

Model Number	Input Voltage Range [VDC]		V <sub>OUT</sub>	l <sub>out</sub>	Efficiency [%] Typ.		Capacitive Load	
Model Nullibel	Nominal	Min.	Max.	[VDC]	[mA] Max.	Min. V <sub>IN</sub>	Max. V <sub>IN</sub>	[uF] Max.
RM10SN-033	24	6	36	3.3	1000	90	80	680
RM10SN-050	24	8	36	5	1000	93	85	680
KWT02N-020	12	8	27	-5	-500	85	81	330
RM10SN-065	24	10	36	6.5	1000	93	85	680
RM10SN-090	24	13	36	9	1000	94	89	680
RM10SN-120	24	16	36	12	1000	95	92	680
KWIUSN-IZU	12	8	20	-12	-300	88	87	330
RM10SN-150	24	20	36	15	1000	96	93	680
KWT09N-120	12	8	18	-15	-300	87	88	330

<sup>\*</sup> Only typical models are listed. Contact our sales agent for availability of other models.



## 1.0A, Non-isolated SIP Package Switching Regulators

## Electrical Specifications

Unless otherwise indicated, specifications are measured at T<sub>A</sub>=25°C, nominal input voltage, full load after warm up.

Parameters	Conditions	Min.	Тур.	Max.	Unit	Note
No load input current $V_{IN} = Min.$ to Max.	Positive Out Negative Out	-	0.3 1.0	1.0 4.0	mA	
Output voltage accuracy Full load	RM10SN-033 Others	-	±2 ±1.5	±4 ±3	%	
Line regulation	V <sub>IN</sub> = Min. to Max.	-	±0.2	±0.4	%	
Load regulation I <sub>DUT</sub> = 10%~100%	Positive Out Negative Out	-	±0.4 ±0.4	±0.6 ±0.8	%	
Temperature coefficiency	-40°C~+85°C	-	-	0.03	%/°C	
Output ripple and noise 20MHz bandwidth, peak to peak		-	25	75	mV	
Dynamic load response lout=25%~50%~75% of lout, rated	Peak deviation Recovery time	-	60 0.2	200 1	mV mS	
Output short circuit protection		Continuous, automatic recovery				
Input filter		Capacitor				

## General Specifications

Parameters	Conditions	Min.	Тур.	Max.	Unit	Note
Operating temperature		-40	-	+85	°C	
Storage temperature		-55	-	+125	°C	
Storage humidity	Non-condensing	5	-	95	%RH	
Switching frequency	Full load	-	600	-	KHz	
Pin soldering resistance 1.5mm away from case for 10 sec		-	-	260	°C	
Cooling method		Free air co	onvection			
Case material		Black plas	tic UL94-V0	)		
Design based on standards		UL/EN/IEC	62368-1			
Safety certifications		EN 62368	-1			
ЕМС	Emissions Immunity		EN55032 CI 000-4-2, 3,	-	ernal circuit r	required)
MTBF MIL-HDBK-217F		>2,000,000 Hours, T <sub>A</sub> =25°C				
Size & Weight		11.60 x 7.	55 x 10.16 r	mm, 1.8g Ty	rp.	

V1.81 04/2024 www.favotek.com




### 1.0A, Non-isolated SIP Package Switching Regulators

### Characteristic Curves


### **Derating Curve**

### **Output vs Ambient Temperature**




### Efficiency vs Input Voltage

### Full Load, RM10SN-050



### Efficiency vs Load

### Nominal input voltage, RM10SN-050





### 1.0A, Non-isolated SIP Package Switching Regulators

### Recommended External Circuit

#### **Typical Application Circuit**




Figure 1: positive output application




Figure 3: dual output application

#### 

Figure 2: negative output application

#### Notes

- C1, C2, C3, C4 are ceramic capacitors, and mandatory for operating of the converters. They can also be tantalum or low ESR electrolytic capacitors. Recommended specs listed in the table on right can be changed according to the needs in the circuits. Recommended LDM is 10uH.
- 2. The converter can be used both for positive and negative output using the circuit connection shown above.
- These converters are not allowed to use in parallel or hot plug without support from properly designed external circuits.

#### [Table 1] Recommended component specifications

Model Number	C1, C3	C2, C4	
RM10SN-033	10uF, 50V	22uF, 10V	
RM10SN-050	10uF, 50V	22uF, 10V	
RM10SN-065	10uF, 50V	22uF, 16V	
RM10SN-090	10uF, 50V	22uF, 16V	
RM10SN-120	10uF, 50V	22uF, 25V	
RM10SN-150	10uF, 50V	22uF, 25V	

#### Circuit for EMC Enhancement

\* This application circuit is recommended in order to meet EN55032 Class B




Figure 4: circuit diagram for positive output



1.0A, Non-isolated SIP Package Switching Regulators

## Recommended External Circuit (continued)

### [Table 2] Recommended component spec


Positive output				
Item	Recommended spec			
MOV	20D470K			
LDM1	82uH			
CO	680uF, 50V			
LCM1	4.7mH			
C1, C2	4.7uF, 50V			
C3	Refer to the C2 in "Table 1"			


Note: The recommended component values are for reference, can be changed according to design needs.




## 1.0A, Non-isolated SIP Package Switching Regulators

### **Mechanical Specifications**







#### Pin Definition

Pin #	Positive Out	Negative Out
1	+V <sub>IN</sub>	+V <sub>IN</sub>
2	GND	-V <sub>OUT</sub>
3	+V <sub>OUT</sub>	GND

- \* Unless otherwise specified unit: mm [inch]
- \* General tolerance: ±0.50 [±0.020]
- \* Pin thickness tolerance: ±0.10 [±0.004]
- \* Footprint grid: 2.54 x 2.54 mm

#### **FAVOTEK LIMITED**

#17 Canton Road, Tsim Sha Tsui, Kowloon, Hong Kong Tel: +852 8191 6662 Eml: info@favotek.com Favotek reserves the right to make changes to the product at any time without notice. Information provided by Favotek is believed to be accurate and reliable. However, no responsibility is assumed by Favotek for its use, nor for any infringements of patents or other rights of third parties which may result from its use.