



| | |
|------------------|------|
| Weight(g) | 47g |
| Torque(kg)(4.8v) | 5.5 |
| Speed(sec/60deg) | 0.2 |
| A(mm) | 44.1 |
| B(mm) | 40.7 |
| C(mm) | 38 |
| D(mm) | 20 |
| E(mm) | 55 |
| F(mm) | 27.8 |

Weight: 47g

Dimension: 40.6×20.5×38mm

Stall torque: 5.5kg/cm(4.8v); 6.5kg/cm(6v);

Operating speed: 0.19sec/deg (4.8v) 0.15sec/deg (6.0v)

Operating voltage: 4.8-6v

Temperature range: 0°C_ 55°C

Gear Type: nylon gear

Temperature range: 0- 55deg

Servo Plug: JR (Fits JR and Futaba)

Dead band width: 1us

servo wire length: 32cm

servo arms & screws included and fit with Futaba servo arm

It's universal "S" type connector that fits most receivers, including Futaba, JR, Hitec ,GWS, Cirrus, Blue Bird, Blue Arrow, Corona, Berg, Spektrum.